

## TR08 SMS Command List

	Features		SMS Command		Remarks
			<i>sms</i>	<i>replies</i>	
1	<b>Mode</b>	set working mode	mode,password,n	Work mode setting ok!	for example: mode,123456,0 (0--power saving mode 1--standard mode,2--tracking mode,3--lbs mode )
3	<b>Admin</b>	set center number	Admin,password,n	Admin phone number setting ok!	for example: Admin,123456,1,13421342519 (n=1~3 Admin,123456,1,d ---delete first admin number)
4	<b>Timezone</b>	set timezone	TimeZone,password,your timezone	Timezone setting ok!	Timezone,123456,8.0 Timezone,123456,5.5 (half time zone)
5	<b>Interval</b>	set updating time interval	Interval,password,m,n	Upload interval setting ok!	interval,123456,30,30 (m,n:0~4294967295 unit: s)
6	<b>Monitor</b>	set monitor number	Monitor,password,phone number	Monitor phone number setting ok!	Monitor,123456,13421342519 Monitor,123456,d delete monitoring number
7	<b>Speed</b>	set over speed alarm	Speed,password,n	Overspeed alarm setting ok!	Speed,123456,90 ( n:0~200 Km/h )

8	<b>GEO</b>	set geo fence	GEO,password,radius	Out geofence alarm setting ok!	<b>GEO,123456,5000</b> <b>GEO,123456,0</b> delete geo fence
9	<b>Password</b>	change password	Password,old password,new password	Password setting ok!	<b>Password,123456,888888</b>
10	<b>APN</b>	set apn	APN,password,apn name,user name,password	APN setting ok!	<b>APN,123456,cmnet</b>
11	<b>IP</b>	set server ip	IP,password,IP address/domain,port	IP and port setting ok!	<b>IP,123456,120.24.83.93,8011</b> or <b>IP,123456,www.xytracking.net,8011</b>
13	<b>Param</b>	check parameter of device	Param,password	SN/IP/APN/SOS Number/Time zone ID:860016020051152 IMEI:860016020051152 APN:null IP:114.119.8.200:88 Interval:30(AccOn),300(AccOff) MODE:1 GPRS ENABLE:1 Time zone:8.0 Admin[1]:18688317590Admin[2]: Admin[3]:	<b>Param,123456</b>
14	<b>Status</b>	check statue of device	Status,password	Ver/Vbat/GSM Signal/GPRS link/GPS signal ID:860016020051152 ACC:0 Mileage:308 V-bat:4.17V GSM:100 GPS Sat:13	<b>Status,123456</b>

15	<b>Restore</b>	factory restore	Restore,password	Reset factory ok!	<b>Restore,123456</b>
16	<b>Reset</b>	reset setting	Reset,password	Reset ok!	<b>Reset,123456</b> 。
17	<b>Loc</b>	check location	Loc,password	replies with address details	<b>Loc,123456</b>
18	<b>URL</b>	check google map link	Url,password	link of google map URL, Get Location OK, 4. 18V, 2017-01-16 11:03:44 http://maps.google.com/?q=loc:+23.092316,+114.429396	<b>Url,123456</b>
20	<b>VER</b>	check version	ver,password	ID:860016020202060 IMEI:860016020202060 Ver:V5.2.0 Build:2017/01/13 16:36 Modal:EASYROAD61D_11C_HW	<b>ver,123456</b>
21	<b>dvd</b>	cut off oil	dvd,password#	DVD=Success!	<b>dvd,123456#</b>
22	<b>hfyd</b>	restore oil	hfyd,password#	HFYD=Success!	<b>hfyd,123456#</b>
23	<b>lanague</b>	change lanague	lang,123456,1 english: lang,123456,0 chinese		
<b>Default password:123456</b>					